

## DIGIDIM Infrared Remote Control (303)

The DIGIDIM Infrared Remote Control is a DIGIDIM-compatible unit for controlling or configuring a DIGIDIM lighting control system. Helvar's DIGIDIM control panels and sensors are fitted with an infrared receiver that allows them to be used in conjunction with the remote control.

This hand-held unit is fitted with seven buttons that control basic system functions such as on/off, raising and lowering the general light level and the selection of four scenes. The styling has been revised for 2016.

Basic programming functions can be performed with combinations of button presses. This includes address-specific preset levels and scene settings.

### Key Features

- Controls basic system functions.
- Programming tool for simple lighting systems (Helvar's Designer or Toolbox software is used for advanced programming).
- Up to four lighting groups can be programmed.
- Can be used for setting scene fade time.

### Additional Features

- Address switch permitting the use of multiple remotes and receivers, without cross interference, within one area. (The receivers must be programmed using Helvar's Designer or Toolbox software.)
- Can control up to four lighting groups: on/off/up/down.



## Technical Data

**Batteries:** 2 × IEC, LR03/AAA 1.5 V battery  
*Note: Batteries are included.*

**Operating range:** Approximately 5 m

**IR frequency:** 36 kHz

### Mechanical data

**Dimensions:** 40 mm × 145 mm × 15 mm

**Housing:** Black, nonflammable polycarbonate, halogen free

**Weight:** 50 g

### Operating conditions

**Ambient temperature:** 0 °C to +40 °C

**Relative humidity:** Max. 90 %, noncondensing

**Storage temperature:** -10 °C to +70 °C

### Conformity and standards

**Environment:** Complies with WEEE and RoHS directives.

### Dimensions (mm)

